



1. **Intrinsic Safety System Certificate.**
2. **Equipment intended for use in potentially explosive atmospheres**
3. **Certificate Number:** ExVeritas 14ATEX0427X **Issue:** 1
4. **Equipment:** HFS FP Series Level Switches
5. **Customer:** Deeter Electronics Limited
6. **Address:** Deeter House, Valley Road,
Hughenden Valley, Bucks. HP14 4LW
7. **This equipment and any acceptable variation thereto are specified in the schedule to this certificate and the documents therein referred to. The assessments are recorded in ExVeritas project file number 0427.**
8. **The equipment has been assessed against the requirements of the EN/IEC 60079-25 at the latest edition for intrinsically Safe Systems and found to comply.**
9. **ExVeritas takes no responsibility for the validity of any information or data supplied by the manufacturer on which parts of the assessment may be based upon**
10. **System Suitability:** See system description

On behalf of ExVeritas

A handwritten signature in blue ink, appearing to read 'D'Henin', is written over a large, faint, light-colored 'V' watermark that spans the background of the lower half of the page.

Stephen D'Henin
Certification Manager

Issue Date: 11/05/2015

This certificate may only be reproduced in its entirety and without any change.
The certificate is only valid when it carries an original signature.
For help or assistance relating to this certificate, contact: info@exveritas.com or view www.exveritas.com



11. **Schedule**

12. **Certificate Number**

ExVeritas 14ATEX0427X

Issue: 1

13. **System Description**

This certificate covers the HFS FP Series Float Switches as Simple Apparatus when coupled with a suitably certified Intrinsically Safe Barrier.

Models HFS FP 50A01, HFS FP 50A02, HFS FP 10C01 and HFS FP 10C02 (without DIN plugs) can be considered for the following systems:

II 1 G IIC T4 Ga	Tamb -20°C to +100°C
II 1 G IIC T6 Ga	Tamb -20°C to +60°C
II 1 D IIIC T135°C	Tamb -20°C to +100°C
II 1 D IIIC T85°C Da	Tamb -20°C to +60°C

Models HFS FP 50A02Din and HFS FP 10C02Din can be considered for the following systems:

II 1 G IIA T4 Ga	Tamb -20°C to +100°C
II 1 G IIA T6 Ga	Tamb -20°C to +60°C
II 1 D IIIA T135°C	Tamb -20°C to +100°C
II 1 D IIIA T85°C Da	Tamb -20°C to +60°C

The simple apparatus assessment of the HFS FP Series Switches can be found in ExVeritas report EVR0427/A. The equipment conformed to all relevant requirements of BS EN 60079-11:2012 for IIA/IIC T4/T6 and IIIA/IIIC T135°C/T85°C use and has the following parameters for consideration when integrated into a system:

Capacitance of the switch 1pF MAX
Resistance of the switch 250 mΩ MAX

14. **Example system**

MTL 7767+ Zener Barrier having the following parameters for IIC/IIIC applications:
Uo = 15V, Io = 150mA, Po = 0.56W, Co = 0.58μF and Lo = 1.45 mH

Coupled with BS5308 Pt 1 Type B cable allows a maximum cable length of 2900m

II 1 G IIC T6 Ga	Tamb -20°C to +60°C
II 1 D IIIC T85°C Da	Tamb -20°C to +60°C



11. **Schedule (continued)**

12. **Certificate Number**

ExVeritas 14ATEX0427X

Issue: 1

15. **Descriptive Documents**

Issue 0

Title	Number	Date	Rev
HFS FP 50A01 Sheets 1 to 2	Dwg631642	14 th July 2014	1
HFS FP 50A02 Sheets 1 to 2	Dwg631643	14 th July 2014	1
HFS FP 50A02Din Sheets 1 to 2	Dwg631644	14 th July 2014	1
HFS FP 10C01 Sheets 1 to 2	Dwg631645	14 th July 2014	1
HFS FP 10C02 Sheets 1 to 2	Dwg631646	14 th July 2014	1
HFS FP 10C02Din Sheets 1 to 2	Dwg631647	14 th July 2014	1

Issue 1

Title	Number	Date	Rev
HFS FP 50A01 Sheets 1 to 2	Dwg631642	11 th May 2015	2
HFS FP 50A02 Sheets 1 to 2	Dwg631643	11 th May 2015	2
HFS FP 50A02Din Sheets 1 to 2	Dwg631644	11 th May 2015	2
HFS FP 10C01 Sheets 1 to 2	Dwg631645	11 th May 2015	2
HFS FP 10C02 Sheets 1 to 2	Dwg631646	11 th May 2015	2
HFS FP 10C02Din Sheets 1 to 2	Dwg631647	11 th May 2015	2



16. Special Conditions of System Certification

- i. The barrier shall be mounted in the safe area and the enclosure shall bear the marking "Warning – Contains intrinsically safe circuits".
- ii. Any cable terminations within the hazardous area shall be made in suitable enclosures providing a degree of protection of at least IP54 and shall bear the marking "Warning – Contains intrinsically safe circuits".
- iii. Terminations shall be made in compliance with the requirements of EN 60079-11. If non-intrinsically safe circuits are also within the enclosure minimum of 50mm clearance shall be employed between the intrinsically safe and non-intrinsically safe circuits.
- iv. The equipment and barrier shall be suitably bonded to a safety earth connection with a resistance of less than 1 ohm. The system installation shall be such that the circuit is bonded to a single reference point only.
- v. The temperature of the process medium shall be considered as part of the ambient temperature range

17. Certificate Revision History

Project File No.	Cert Issue Date	Issue	Comment
0427	21/01/2015	0	Initial issue of the Prime Certificate
0608	11/05/2015	1	Company name changed from 'Deeter Engineering Services Ltd' to 'Deeter Electronics Ltd'. Drawings revised to Rev 2 to amend the drawing templates to show the name change. No change to the technical content.